

## DMX functions

**DUNE FC 12 AL1760**

**DUNE FC 28 AL1762**

**DUNE FC 40 AL1764**

**DMX functions with 62 PRESET COLOURS = OFF**

Channel	Function	Value	Description
1	Red	0-255	0-100% Proportional colour control
2	Green	0-255	0-100% Proportional colour control
3	Blue	0-255	0-100% Proportional colour control
4	Blackout Dimmer Strobe	0-15	100% Luminous output intensity
		16-160	100-0% Proportional control of the luminous output intensity
		161-255	Proportional control of the Strobe effect

**DMX functions with 62 PRESET COLOURS = ON**

Channel	Function	Value	Description
1	62 Preset colours	0-255	62 Preset colours selection (4 DMX value step)
2	Blackout Dimmer Strobe	0-15	100% Luminous output intensity
		16-160	100-0% Proportional control of the luminous output intensity
		161-255	Proportional control of the Strobe effect